

# PHILIPS



Compatibility List Professional Q2 2026

## Low Voltage / Dimmer

### Table of contents

Professional transformer compatibility  
list LED Low Voltage range

[2](#)

Professional dimmer transformer compatibility  
list LED Low Voltage range

[8](#)














# Professional transformer compatibility list LED Low Voltage range

Recommended transformer compatibility list for Low Voltage lamps  
For non-dimmable systems only

Key

x-y	Transformer is compatible with x - y lamp	This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab conditions and might contain faults.
x-y	Transformer is compatible but will not work according Philips claimed specifications under all conditions	
	Transformer is not compatible and therefore will not comply to Philips claimed specifications	
N.A.	Transformer lamp combination not applicable/relevant	
T.B.D.	Transformer lamp combination not tested	

				LED Bulb						
				MAS ExpertColor 10.8-50W AR111  9290030432 9290030433 9290030434 9290030435 9290030436 9290030437	MAS ExpertColor 14.8-75W AR111  9290030426 9290030427 9290030428 9290030429 9290030430 9290030431	MAS LEDExpertColor 20-100W AR111 24D  9290034786 9290034787 9290034788 9290034789 9290034790 9290034791	12-75W AR111 3000K 9D D  9290044579	CorePro LEDspot 10-75W 830 AR111 40D  9290029651	CorePro LEDspot 14-100W 830 AR111 40D  9290029652	CorePro LEDspot 7-50W 830 AR111 40D  9290029650
				 	 	 	 			
Transformer 10-70W	Brand/type	Watt	LED Watt							
	Philips Primaline 70	20-70	4-14	1	1	1	1	1	1	1-2
	OSRAM Halotronic HTM 70 (new type)	20-70	4-14	1	1	1	1	1	1	1-2
	Philips ET-S60	20-60	4-12	T.B.D.	N.A.	N.A.	1	T.B.D.	N.A.	N.A.
	Philips Certaline 60	20-60	4-12	1	1	1	1	1	1	1-2
	SEET STE 70VA 7429	20-70	4-14	1	1	1	1	1	1	1
	TCI PICO WOLF 60	10-60	4-12	1	N.A.	1	2	2	N.A.	2
	Vossloh Schwabe EST 60/12.635	10-60	4-12	1	N.A.	1	1	1	N.A.	
	RELCO ICE60 PFS TH 60W	10-60	4-12	1	N.A.	1	1	1	N.A.	1
	Varilight YT50L	0-50	0-10	1	1	1	1	1	1	1-2
	Varilight YT70L	0-70	0-14	1	1	1	1	1	1	1-2
	Vossloh Schwabe EST 70/12.380	20-70	4-14	1	1	1	1	1	1	1
	Paulmann Trafo Halo + LED 0-65W - 97767	20-60	4-12	1-3	1-2	1-2	1	1-4	1-2	1-4
	Govena YT60	20-70	4-14	1	1	1	1	1-2	1	1-2
	SLV 461060 Micro 60 PFS	20-60	4-12	1	1	1	1	1	1	1
	Osram 111593 ET PARROT 70/220-240	10-60	4-12	1	1	1	1	1-2	1	1
	TCI 119617 ROUND 70	20-70	4-14	1	1	1	1	1-2	1	1
	EVN TAB 70 (3310)	20-70	4-14	1	1	1	1	1-2	1	1
	EVN MINIJOKER 70(T27/10)	10-70	2-14			1	1	1-2	1	1
	Niko 320-00121	10-65	0-40	1	1	1	1	1-2	1	1
Transformer 20-105W	Philips Primaline 105	35-105	7-20	1	1	1	1	1-2	1	1-3
	OSRAM Halotronic HTM 105	35-105	7-20	1	1	1	1	1-2	1	1-3
	Philips Certaline 105	35-105	7-20	1	1	1	N.A.	1-2	1	1-3
	RELCO ICE 105 PFS TH	20-105	4-20	1-2	1	1	1	1-2	1	1-2
	Vossloh Schwabe EST 105	20-105	4-20	1-2	1	1	1	1-2	1	1-2
	Varilight YT105L	0-105	0-20	1-2	1	1	1	1-2	1	1-2
	OSRAM ET-PARROT 105	35-105	7-20	1-2	1	1	1	1-3	1	1-2
	Govena YT105	35-105	7-20	1-3	1-2	1-2	1	1-5	1-2	1-4
	Osram 927019 HTL 105/230-240	35-105	7-20	1-2	1	1	1	2-3	1	1-2
	TCI Pico Wolf 105	20-105	4-20	1-2	1	1	1	1-2	1	1-2
	GIRA tronic trafo	20-105	4-20	1-2	1	1	1	1-2	1	1-2
	Osram HTI DALI 105/230...240 DIM+Dyna lite DDBC120-DALI	35-105	7-20	2-7	2-6	2-4	N.A.	N.A.	N.A.	N.A.
Transformer 50-150W	Philips Primaline 150	50-150	10-30	1-2	1-2	1	N.A.	1-3	1-2	1-3
	OSRAM HTM 150	50-150	10-30	1-2	1-2	1				
	Varilight YT150	0-150	0-30	1-3	1-2	1	1- 2	1-3	1-2	1-3
	SLV TRANSFORMATEUR, 12V AC, 150VA,	50-150	10-30	1-2	1	1	1- 2	1-4	1-2	1-3
	TCI Wolf 150, WX 150	50-150	10-30	2	2	1	2	2-4	1-2	1-3
	Jung SNT150	50-150	10-30	2	1-2	1		1-4	1-2	1-3
	RELCO RN1684 FOX 150 PFS TH	50-150	10-30	1	1	1	2	1	1	1
Trans-former 50-250W	RELCO ICE 200 PFS TH	100-200	20-40	2-4	2	1-2	1-3	2-4		3-5
	Osram 927026 HTL 225/230-240	50-225	10-45	2-4	2-3	2	2-3	2-6	2- 3	2-4






# Professional transformer compatibility list LED Low Voltage range

Recommended transformer compatibility list for Low Voltage lamps  
For non-dimmable systems only

Key

x-y	Transformer is compatible with x - y lamp
x-y	Transformer is compatible but will not work according Philips claimed specifications under all conditions
	Transformer is not compatible and therefore will not comply to Philips claimed specifications
N.A.	Transformer lamp combination not applicable/relevant
T.B.D.	Transformer lamp combination not tested

This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab conditions and might contain faults.

				LED Bulb				
				MAS LEDspotLV D 7.5-50W MR16	MAS LED ExpertColor 6.7-35W MR16	MAS LED ExpertColor 7.5-43W MR16	MAS LEDspotLV 3.5-20W 827 MR11 24D	CorePro LED spot ND 2.9-20W MR16 827 36D
				9290024919 9290024920 9290024921 9290024922 9290024923 9290024924	9290030785 9290030786 9290030787 9290030788 9290030789 9290030790 9290030791 9290030792 9290030793 9290030794 9290030795 9290030796	9290030797 9290030798 9290030799 9290030800 9290030801 9290030802	9290030870	9290024945
				 Dimmable	 Dimmable	 Dimmable		
				Brand/type	Watt	LED Watt		
Transformer 10-70W	Philips Primaline 70	20-70	4-14	1	1-2	1	2-4	1-5
	OSRAM Halotronic HTM 70 (new type)	20-70	4-14	1	1	1	1-4	1-5
	Philips ET-S60	20-60	4-12	1	1-2	1	T.B.D.	T.B.D.
	Philips Certaline 60	20-60	4-12	1	1	1	1-4	1-4
	SEET STE 70VA 7429	20-70	4-14	1	1-2	1	T.B.D.	1-5
	TCI PICO WOLF 60	10-60	4-12			2		1-4
	Vossloh Schwabe EST 60/12.635	10-60	4-12	1	1-2	1	1-4	1-3
	RELCO ICE60 PFS TH 60W	10-60	4-12	1	1-2	1	2-4	1-4
	Varilight YT50L	0-50	0-10	1	N.A.	N.A.	T.B.D.	1-3
	Varilight YT70L	0-70	0-14	1	1	1	1-4	1-5
	Vossloh Schwabe EST 70/12.380	20-70	4-14	1	1-2	1	1-4	1-2,3
	Paulmann Trafo Halo + LED 0-65W - 97767	20-60	4-12	1-4	1-5	1-4	1-11	1-5
	Govenia YT60	20-70	4-14	1-2	1-2	1-2	1-4	1-5
	SLV 461060 Micro 60 PFS	20-60	4-12	1-6	1-7	1-6	1-4	1-4
	Osram 111593 ET PARROT 70/220-240	10-60	4-12	1-6	1-7	1-6	T.B.D.	T.B.D.
	TCI 119617 ROUND 70	20-70	4-14	1-8	1-9	1-8	1-4	1-5
	EVN TAB 70 (3310)	20-70	4-14	1-8	1-9	1-8	1-4	1-5
	EVN MINIJOKER 70(T27/10)	10-70	2-14	2-7	2-8	2-7		T.B.D.
	Niko 320-00121	10-65	0-40	1-5	1-6	1-5	1-4	1-2
Transformer 20-105W	Philips Primaline 105	35-105	7-20	1-2	1-2	1-2	1-6	2-5
	OSRAM Halotronic HTM 105	35-105	7-20	1-2	1-2	1-2	1-6	T.B.D.
	Philips Certaline 105	35-105	7-20	1-2	1-2	1-2	2-5	1-5
	RELCO ICE 105 PFS TH	20-105	4-20	1-2	1-3	1-2	1-6	
	Vossloh Schwabe EST 105	20-105	4-20	1-2	1-3	1-2	1-6	1-5
	Varilight YT105L	0-105	0-20	1-2	1-3	1-2	1-6	1-5
	OSRAM ET-PARROT 105	35-105	7-20	1-8	1-9	1-8	1-6	1-5
	Govenia YT105	35-105	7-20	1-4	1-5	1-4	1-6	1-5
	Osram 927019 HTL 105/230-240	35-105	7-20	1-10	1-11	1-10	2-6	T.B.D.
	TCI Pico Wolf 105	20-105	4-20	1-2	1-3	1-2	2-6	1-2,3
	GIRA tronic trafo	20-105	4-20	1-2	1-3	1-2	3-6	1-5
	Osram HTI DALI 105/230...240 DIM+Dynalite DDBC120-DALI	35-105	7-20	3-9	2-10	3-10	N.A.	N.A.
Transformer 50-150W	Philips Primaline 150	50-150	10-30	1-3	1-3	1-3	1-8	T.B.D.
	OSRAM HTM 150	50-150	10-30	1-3	1-2	1-9	2-8	1-5
	Varilight YT150	0-150	0-30	1-3	1-5	1-3	1-8	1-5
	SLV TRANSFORMATEUR, 12V AC, 150VA,	50-150	10-30	1-15	1-16	1-15	T.B.D.	1-5
	TCI Wolf 150, WX 150	50-150	10-30	2-14	2-16	2-14	T.B.D.	2-5
	Jung SNT150	50-150	10-30	1-15	1-17	1-15	1-8	1,5
	RELCO RN1684 FOX 150 PFS TH	50-150	10-30	1-7	1-8	1-7	3-8	1-5
Trans- former 50- 250W	RELCO ICE 200 PFS TH	100-200	20-40	3-5	4-6	3-5		
	Osram 927026 HTL 225/230-240	50-225	10-45	2-20	2-20	2-20	3-12	1-5







# Professional transformer compatibility list LED Low Voltage range

Recommended transformer compatibility list for Low Voltage lamps  
For non-dimmable systems only

Key

x-y	Transformer is compatible with x - y lamp
x-y	Transformer is compatible but will not work according Philips claimed specifications under all conditions
	Transformer is not compatible and therefore will not comply to Philips claimed specifications
N.A.	Transformer lamp combination not applicable/relevant
T.B.D.	Transformer lamp combination not tested

This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab conditions and might contain faults.







				LED Bulb					
				CorePro LED spot ND 4.4-35W MR16 827 36D  CorePro LEDspot 4.4-35W MR16 827 36D 5CT  9290024946 	CorePro LED spot ND 4.4-35W MR16 840 36D  CorePro LED spot ND 4.4-35W MR16 840 36DUK  9290024947 	CorePro LED spot ND 7-50W MR16 36D  9290019048 9290019049 9290019050 	CorePro LED spot 2.3-20W 827 MR11 36D  9290020664 	MAS LED spot VLE D 5.8-35W MR16  9290024925 9290024926 9290024927 9290024928 9290024929 9290024930  Dimmable	MAS LEDspot LV DimTone 5.8-35W MR16 36D  9290024931  Dimmable
Transformer 10-70W	Brand/type	Watt	LED Watt						
	Philips Primaline 70	20-70	4-14	1-3	1-3	2	1-6	1-3	1-3
	OSRAM Halotronic HTM 70 (new type)	20-70	4-14	1-3	1-3	1	1-6	1-3	1-3
	Philips ET-S60	20-60	4-12	T.B.D.	T.B.D.	1	T.B.D.	T.B.D.	T.B.D.
	Philips Certaline 60	20-60	4-12	1-2	1-2	1	2-5	1-3	1-3
	SEET STE 70VA 7429	20-70	4-14	1-3	1-3	1	T.B.D.	1-2	1-2
	TCI PICO WOLF 60	10-60	4-12				3-5	2	2
	Vossloh Schwabe EST 60/12.635	10-60	4-12	1-2	1-2		1-5	1-2	1-2
	RELCO ICE60 PFS TH 60W	10-60	4-12	1-2	1-2	1	2-5	1-2	1-2
	Varilight YT50L	0-50	0-10	1-2	1-2	1-2	1-2	1-3	1-2
	Varilight YT70L	0-70	0-14	1-3	1-3	1-2	1-2	1-3	1-3
	Vossloh Schwabe EST 70/12.380	20-70	4-14	1-3	1-3	1-2	1-2	1,2	1-2
	Paulmann Trafo Halo + LED 0-65W - 97767	20-60	4-12	1-5	1-5	1-2	1-2	1-6	1-6
	Govena YT60	20-70	4-14	1-4	1-4	1-2	1-5	1-3	1-3
	SLV 461060 Micro 60 PFS	20-60	4-12	1-3	1-3	1	1-5	1-2	1-2
	Osram 111593 ET PARROT 70/220-240	10-60	4-12	T.B.D.	T.B.D.		T.B.D.		
	TCI 119617 ROUND 70	20-70	4-14	1-3	1-3	1-2	1-6	1-2	1-2
	EVN TAB 70 (3310)	20-70	4-14	1-3	1-3	1-2	1-6	1-2	1-2
	EVN MINIJOKER 70(T27/10)	10-70	2-14	T.B.D.	T.B.D.	2	1-6	2	2
	Niko 320-00121	10-65	0-40	1-2	1-2	1	1-6	1-2	1-2
Transformer 20-105W	Philips Primaline 105	35-105	7-20	1-4	1-4	1,3	1-9	1-4	1-4
	OSRAM Halotronic HTM 105	35-105	7-20	1-4	1-4	1-3	1-9	1-4	1-4
	Philips Certaline 105	35-105	7-20			1-3	1-8	1-4	1-4
	RELCO ICE 105 PFS TH	20-105	4-20				1-9	1-3	1-3
	Vossloh Schwabe EST 105	20-105	4-20	1-4	1-4	1-2	1-9	1-3	1-3
	Varilight YT105L	0-105	0-20	1-4	1-4	1-2	1-9	1-3	1-3
	OSRAM ET-PARROT 105	35-105	7-20	1-4	1-4	1-3	1-9	1-3	1-3
	Govena YT105	35-105	7-20	1-5	1-5	1-5	1-9	1-6	1-6
	Osram 927019 HTL 105/230-240	35-105	7-20	T.B.D.	T.B.D.	2-3		1-3	2-3
	TCI Pico Wolf 105	20-105	4-20	1-2, 4	1-2,4	2	2-9	1-3	2-3
	GIRA tronic trafo	20-105	4-20	1-4	1-4	2	3-9	1-3	1-3
	Osram HTIDALI 105/230...240 DIM+Dynalite DDBC120-DALI	35-105	7-20	N.A.	N.A.		N.A.	3-10	3-11
Transformer 50-150W	Philips Primaline 150	50-150	10-30	T.B.D.	T.B.D.	2-4	2-3, 5-6	1-4	1-6
	OSRAM HTM 150	50-150	10-30	1-5	1-5	2-4	1-13	2-4	2-6
	Varilight YT150	0-150	0-30	1-5	1-5	1-3	1-13	1-5	1-5
	SLV TRANSFORMATEUR, 12V AC, 150VA,	50-150	10-30	1-5	1-5	1-4	T.B.D.	1-5	1-5
	TCI Wolf 150, WX 150	50-150	10-30	1-5	1-5	2-4	T.B.D.	2-5	2-5
	Jung SNT150	50-150	10-30	1	1	2-4	1-13	1-5	2-5
	RELCO RN1684 FOX 150 PFS TH	50-150	10-30	1-5	1-5		3-13	1-2	1-2
Trans-former 50-250W	RELCO ICE 200 PFS TH	100-200	20-40					4-6	4-6
	Osram 927026 HTL 225/230-240	50-225	10-45	1-5	1-5	2-6	1-14	2-7	2-7

# Professional transformer compatibility list LED Low Voltage range

Recommended transformer compatibility list for Low Voltage lamps  
For non-dimmable systems only

Key

x-y	Transformer is compatible with x - y lamp	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab conditions and might contain faults.</i>
x-y	Transformer is compatible but will not work according Philips claimed specifications under all conditions	
	Transformer is not compatible and therefore will not comply to Philips claimed specifications	
N.A.	Transformer lamp combination not applicable/relevant	
T.B.D.	Transformer lamp combination not tested	





				LED Bulb		
				MAS LEDspotLV DimTone 5-35W MR16 36D  9290019047   	MAS LED SPOT VLE D 7.5-50W MR16  9290024932 9290024933 9290024934 9290024935 9290024936 9290024937   	MAS LEDspot LV DimTone 7.5-50W MR16 36D  9290024938   
Transformer 10-70W	Brand/type	Watt	LED Watt			
	Philips Primaline 70	20-70	4-14		1-2	1
	OSRAM Halotronic HTM 70 (new type)	20-70	4-14	1-2	1-2	1
	Philips ET-S60	20-60	4-12	1-2	T.B.D.	T.B.D.
	Philips Certaline 60	20-60	4-12	1-2	1-2	1
	SEET STE 70VA 7429	20-70	4-14	1-2	1	1
	TCI PICO WOLF 60	10-60	4-12	1-2	2	
	Vossloh Schwabe EST 60/12.635	10-60	4-12	1-2	1	1
	RELCO ICE60 PFS TH 60W	10-60	4-12	2	1	1
	Varilight YT50L	0-50	0-10	1-2	1	1
	Varilight YT70L	0-70	0-14	1-2	1	1
	Vossloh Schwabe EST 70/12.380	20-70	4-14	1-2	1-2	1
	Paulmann Trafo Halo + LED 0-65W - 97767	20-60	4-12	1-2	1-5	1-5
	Govena YT60	20-70	4-14	1-2	1-2	1-2
	SLV 461060 Micro 60 PFS	20-60	4-12	1-2	1	1
	Osram 111593 ET PARROT 70/220-240	10-60	4-12	1-2		1
	TCI 119617 ROUND 70	20-70	4-14	2	1	1
	EVN TAB 70 (3310)	20-70	4-14	2	1	1
	EVN MINIJOKER 70(T27/10)	10-70	2-14	2		
	Niko 320-00121	10-65	0-40	1-2	1	1
Transformer 20-105W	Philips Primaline 105	35-105	7-20	1	1-3	1-2
	OSRAM Halotronic HTM 105	35-105	7-20	1-4	1-3	1-2
	Philips Certaline 105	35-105	7-20	1,3-4	1-3	2
	RELCO ICE 105 PFS TH	20-105	4-20	1-4	1-2	2
	Vossloh Schwabe EST 105	20-105	4-20	2-4	1-2	1-2
	Varilight YT105L	0-105	0-20	1-4	1-2	1-2
	OSRAM ET-PARROT 105	35-105	7-20	1-4	1-2	1-2
	Govena YT105	35-105	7-20	1-4	1-5	1-5
	Osram 927019 HTL 105/230-240	35-105	7-20	1-4	2	2
	TCI Pico Wolf 105	20-105	4-20	1-4	1-2	2
	GIRA tronic trafo	20-105	4-20	3-4	1-2	2
	Osram HTI DALI 105/230...240 DIM+Dynalite DDBC120-DALI	35-105	7-20	2-4	2-7	3-13
Transformer 50-150W	Philips Primaline 150	50-150	10-30	1,3-6	1-4	1-3
	OSRAM HTM 150	50-150	10-30	2-6	2-4	2-3
	Varilight YT150	0-150	0-30	1-6	1-3	1-3
	SLV TRANSFORMATEUR, 12V AC, 150VA	50-150	10-30	1-6	1-4	1-4
	TCI Wolf 150, WX 150	50-150	10-30	1,3-6	2-4	3-4
	Jung SNT150	50-150	10-30	3-6	1-4	1-4
	RELCO RN1684 FOX 150 PFS TH	50-150	10-30	1-3, 5-6	1	1
Trans- former 50- 250W	RELCO ICE 200 PFS TH	100-200	20-40	5-8	3-5	3-4
	Osram 927026 HTL 225/230-240	50-225	10-45	2-9	2-6	2-6

# Professional transformer compatibility list LED Low Voltage range

Recommended transformer compatibility list for Low Voltage lamps  
For non-dimmable systems only

Key

x-y	Transformer is compatible with x - y lamp	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab conditions and might contain faults.</i>
x-y	Transformer is compatible but will not work according Philips claimed specifications under all conditions	
	Transformer is not compatible and therefore will not comply to Philips claimed specifications	
N.A.	Transformer lamp combination not applicable/relevant	
T.B.D.	Transformer lamp combination not tested	






				LED Bulb			
				MCorePro LEDcapsuleLV 1-10W G4 827 9290023888  CorePro LEDcapsuleLV 1-10W G4 830 9290023889  LED 10W G4 WH 12V ND SRT6 9290023889	CorePro LEDcapsuleLV 1.8-20W GY6.35 9290023897 9290023898	CorePro LEDcapsuleLV 1.8-20W G4 827 9290023890  CorePro LEDcapsuleLV 1.8-20W G4 830 9290023891  LED 20W G4 WH 12V RF ND SRT6 9290023891	CorePro LEDcapsuleLV 2.1-20W G4 827 D 9290037792
							  Dimmable
Transformer 10-70W	Brand/type	Watt	LED Watt				
	Philips Primaline 70	20-70	4-14	1-10	1-7	1-7	2-6
	OSRAM Halotronic HTM 70 (new type)	20-70	4-14	1-10	1-7	1-7	1-6
	Philips ET-S60	20-60	4-12		T.B.D.	T.B.D.	
	Philips Certaline 60	20-60	4-12	1-10	1-6	1-6	1-5
	SEET STE 70VA 7429	20-70	4-14	1-10	T.B.D.	T.B.D.	1-6
	TCI PICO WOLF 60	10-60	4-12		1-6	1-6	2-5
	Vossloh Schwabe EST 60/12.635	10-60	4-12	1	1-6	1-6	1-5
	RELCO ICE60 PFS TH 60W	10-60	4-12	1-10	1-6	1-6	1-5
	Varilight YT50L	0-50	0-10	1-10	T.B.D.	T.B.D.	1-4
	Varilight YT70L	0-70	0-14	1-10	1-7	1-7	1-6
	Vossloh Schwabe EST 70/12.380	20-70	4-14	1-10	1-7	1-7	1-6
	Paulmann Trafo Halo + LED 0-65W - 97767	20-60	4-12	1-16	1-13	1-13	1-5
	Govena YT60	20-70	4-14	1-20	1-6	1-6	1-5
	SLV 461060 Micro 60 PFS	20-60	4-12	1-12	1-6	1-6	1-5
	Osram 111593 ET PARROT 70/220-240	10-60	4-12	1-7	T.B.D.	T.B.D.	1-6
	TCI 119617 ROUND 70	20-70	4-14	1-5	1-7	1-7	1-6
	EVN TAB 70 (3310)	20-70	4-14	1-4	1-7	1-7	1-6
	EVN MINIJOKER 70(T27/10)	10-70	2-14		1-7	1-7	2-6
	Niko 320-00121	10-65	0-40		1-5	1-5	1-5
Transformer 20-105W	Philips Primaline 105	35-105	7-20	1-10	1-11	1-11	1-10
	OSRAM Halotronic HTM 105	35-105	7-20	1-10	1-11	1-11	1-10
	Philips Certaline 105	35-105	7-20	1-10	1-3	1-3	1-10
	RELCO ICE 105 PFS TH	20-105	4-20	1-10	1-11	1-11	1-10
	Vossloh Schwabe EST 105	20-105	4-20	1-10	1-11	1-11	1-10
	Varilight YT105L	0-105	0-20	1-10	1-11	1-11	1-10
	OSRAM ET-PARROT 105	35-105	7-20	1-21	1-11	1-11	1-10
	Govena YT105	35-105	7-20	1-25	1-11	1-11	1-10
	Osram 927019 HTL 105/230-240	35-105	7-20	1-21	T.B.D.	T.B.D.	2-10
	TCI Pico Wolf 105	20-105	4-20	1	1-11	1-11	2-10
	GIRA tronic trafo	20-105	4-20	1-10	1-11	1-11	3-10
	Osram HTI DALI 105/230...240 DIM+Dynalite DDBC120-DALI	35-105	7-20	N.A.	N.A.	N.A.	4-10
Transformer 50-150W	Philips Primaline 150	50-150	10-30	1-10			2-14
	OSRAM HTM 150	50-150	10-30	1-10	1-16	1-16	3-14
	Varilight YT150	0-150	0-30	1-10	1-16	1-16	1-14
	SLV TRANSFORMATEUR, 12V AC, 150VA	50-150	10-30	1-25	1-16	1-16	1-14
	TCI Wolf 150, WX 150	50-150	10-30	1-25	T.B.D.	T.B.D.	5-14
	Jung SNT150	50-150	10-30		1-16	1-16	1-14
	RELCO RN1684 FOX 150 PFS TH	50-150	10-30	1-9	1-16	1-16	9-14
Trans- former 50- 250W	RELCO ICE 200 PFS TH	100-200	20-40	1-2			6-19
	Osram 927026 HTL 225/230-240	50-225	10-45	1-17	1-20	1-20	3-19

# Professional transformer compatibility list LED Low Voltage range

Recommended transformer compatibility list for Low Voltage lamps  
For non-dimmable systems only

Key

x-y	Transformer is compatible with x - y lamp	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab conditions and might contain faults.</i>
x-y	Transformer is compatible but will not work according Philips claimed specifications under all conditions	
	Transformer is not compatible and therefore will not comply to Philips claimed specifications	
N.A.	Transformer lamp combination not applicable/relevant	
T.B.D.	Transformer lamp combination not tested	

				LED Bulb			
				CorePro LEDcapsuleLV 4.2-40W GY6.35 827D 9290036090	CorePro LEDcapsuleLV 1-10W G4 827micro 9290037789	CorePro LEDcapsuleLV 1.7-20W G4micro 827 9290037790	CorePro LEDcapsuleLV 2.4-28W G4micro 827 9290037791
				 			
Transformer 10-70W	Brand/type	Watt	LED Watt				
	Philips Primaline 70	20-70	4-14	1-3	1-14	1-8	1-5
	OSRAM Halotronic HTM 70 (new type)	20-70	4-14	1-3	1-14	1-8	1-5
	Philips ET-S60	20-60	4-12	T.B.D.	1-2	1-2	1-2
	Philips Certaline 60	20-60	4-12	1-2	1-12	1-7	1-4
	SEET STE 70VA 7429	20-70	4-14	1-2	1-14	1-8	1-5
	TCI PICO WOLF 60	10-60	4-12	2			
	Vossloh Schwabe EST 60/12.635	10-60	4-12	2			
	RELCO ICE60 PFS TH 60W	10-60	4-12	1-2	1-12	1-7	1-4
	Varilight YT50L	0-50	0-10	1-2	1-10	1-6	1-3
	Varilight YT70L	0-70	0-14	1-3	1-14	1-8	1-5
	Vossloh Schwabe EST 70/12.380	20-70	4-14	1-3	1-14	1-8	1-5
	Paulmann Trafo Halo + LED 0-65W - 97767	20-60	4-12	1-9	1-12	1-7	1-4
	Govena YT60	20-70	4-14	1-2	1-12	1-8	1-4
	SLV 461060 Micro 60 PFS	20-60	4-12	1-2	1-12	1-7	1-4
	Osram 111593 ET PARROT 70/220-240	10-60	4-12	1-3	1-12	1-7	1-4
	TCI 119617 ROUND 70	20-70	4-14	1-3	1-7	1-5	1-2
	EVN TAB 70 (3310)	20-70	4-14	1-3	1-8	1-4	1-2
	EVN MINIJOKER 70(T27/10)	10-70	2-14	2-3			
	Niko 320-00121	10-65	0-40	1-3	1-4	1-3	1-2
Transformer 20-105W	Philips Primaline 105	35-105	7-20	1-5	1-7	1-4	1-2
	OSRAM Halotronic HTM 105	35-105	7-20	1-5	1-20	1	1-4
	Philips Certaline 105	35-105	7-20	1-5	1-7	1-12	1-7
	RELCO ICE 105 PFS TH	20-105	4-20	1-5	1-20	1-6	1-7
	Vossloh Schwabe EST 105	20-105	4-20	1-5	1-20	1-12	1-7
	Varilight YT105L	0-105	0-20	1-5	1-20	1-12	1-7
	OSRAM ET-PARROT 105	35-105	7-20	1-5	1-20	1-12	1-7
	Govena YT105	35-105	7-20	1-5	1-20	1-12	1-7
	Osram 927019 HTL 105/230-240	35-105	7-20	2-5	1-20	1-6	1-7
	TCI Pico Wolf 105	20-105	4-20	1-5			
	GIRA tronic trafo	20-105	4-20	2-5			
	Osram HTI DALI 105/230...240 DIM+Dynalite DDBC120-DALI	35-105	7-20	2-15			1-4
Transformer 50-150W	Philips Primaline 150	50-150	10-30	1-7	1-7	1-6	1-7
	OSRAM HTM 150	50-150	10-30	2-7	1-7	1-7	1-8
	Varilight YT150	0-150	0-30	1-7	1-20	1-17	1-12
	SLV TRANSFORMATEUR, 12V AC, 150VA	50-150	10-30	1-7	1-20	1-17	1-12
	TCI Wolf 150, WX 150	50-150	10-30	2-7	1-14	1-17	1-12
	Jung SNT150	50-150	10-30	1-7	1-4	1	1
	RELCO RN1684 FOX 150 PFS TH	50-150	10-30	1-2	1-13	1-6	1-7
Trans- former 50- 250W	RELCO ICE 200 PFS TH	100-200	20-40	4-9			
	Osram 927026 HTL 225/230-240	50-225	10-45	2-10	1-20	1-18	1-18



# Professional dimmer transformer compatibility list LED

## Low Voltage range

Key

#	Transformer - dimmer combination is compatible with # of lamp(s) and minimum dimming level is below 30% AND maximum dimming level is at least 80%.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab conditions and might contain faults.</i>
#	Transformer - dimmer combination is compatible with # of lamp(s) and minimum dimming level is between 30% (inclusive) and 50% AND maximum level is above or equal to 70%.	
	Transformer is not compatible.	
	Transformer lamp combination not applicable	
	Transformer lamp combination not tested	



MAS ExpertColor 10.8-50W 927 AR111  
9290030432, 9290030433, 9290030434, 9290030435, 9290030436, 9290030437

Dimmer	Brand	Model	Load
	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L,C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4 ~ 200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC ] 315W
	Varilight	HQ3W	[R ] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	35 - 105W	50 - 150W	35 - 105W	50 - 150W	0 - 70W	20 - 70W	35-105W	20 - 70W	20 - 105W

1			1		1				
1	1	1-2	1	1	1	1	1-2	1	1-2
1	1	1-2	1	1	1	1	1-2	1	1-2
1	1	1-2	1	1		1	1-2		1-2
				1		1	1-2	1	2
1		1			1	1	1-2	1	1-2
1	1	1-2	1	1	1	1	1-2	1	1-2
1	1	1-2		1	1	1	1-2	1	2
1	1	1-2	1	1	1	1	1-2	1	1-2



MAS ExpertColor 14.8-75W 927 AR111  
9290030426, 9290030427, 9290030428, 9290030429, 9290030430, 9290030431

Dimmer	Brand	Model	Load
	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L,C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4 ~ 200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC ] 315W
	Varilight	HQ3W	[R ] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	35 - 105W	50 - 150W	35 - 105W	50 - 150W	0 - 70W	20 - 70W	35-105W	20 - 70W	20 - 105W

1	1	1	1	1	1	1	1	1	1
		1	1		1	1	1	1	
			1		1	1	1	1	
1			1	1	1	1	1	1	
1	1	1	1	1	1	1	1		1-2
						1	1		
1	1	1	1	1	1	1	1		1-2
1		1	1	1	1	1	1	1	1-2



MAS LEDExpertColor 20-100W 927 AR111 24D  
9290034786, 9290034787, 9290034788, 9290034789, 9290034790, 9290034791

Dimmer	Brand	Model	Load
	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L,C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4 ~ 200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC ] 315W
	Varilight	HQ3W	[R ] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	35 - 105W	50 - 150W	35 - 105W	50 - 150W	0 - 70W	20 - 70W	35-105W	20 - 70W	20 - 105W

1		1			1	1		1	1
		1	1	1	1	1	1	1	
									1
					1	1	1	1	
		1			1	1	1	1	1
				1					
		1		1		1	1	1	1
		1					1		
				1	1	1	1	1	



# Professional dimmer transformer compatibility list LED


## Low Voltage range

Key


#	Transformer - dimmer combination is compatible with # of lamp(s) and minimum dimming level is below 30% AND maximum dimming level is at least 80%.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab conditions and might contain faults.</i>
#	Transformer - dimmer combination is compatible with # of lamp(s) and minimum dimming level is between 30% (inclusive) and 50% AND maximum level is above or equal to 70%.	
	Transformer is not compatible.	
	Transformer lamp combination not applicable	
	Transformer lamp combination not tested	

	<b>12-75W AR111 3000K 9D D</b> 9290044579		
Dimmer	Brand	Model	Load
	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC ] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L,C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4 ~ 200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC ] 315W
	Varilight	HQ3W	[R ] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	35 - 105W	50 - 150W	35 - 105W	50 - 150W	0 - 70W	20 - 70W	35-105W	20 - 70W	20 - 105W
1			1		1	1	1	1	
1	1		1	1	1	1	1	1	
1	1		1	1	1	1	1	1	
1			1	1	1	1	1	1	
1	1		1	1	1	1	1	1	
1	1		1	1	1	1	1	1	
1	1		1	1	1	1	1	1	
1	1		1	1	1	1	1	1	
1	1		1	1	1	1	1	1	
1			1	1	1	1	1	1	
1			1	1	1	1	1	1	

	<b>MAS LEDspotLV D 7.5-43W MR16</b> 9290030797, 9290030798, 9290030799, 9290030800, 9290030801, 9290030802		
Dimmer	Brand	Model	Load
	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC ] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L,C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4 ~ 200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC ] 315W
	Varilight	HQ3W	[R ] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	35 - 105W	50 - 150W	35 - 105W	50 - 150W	0 - 70W	20 - 70W	35-105W	20 - 70W	20 - 105W
1			1		1	1	1 - 2	1	
1	1	2			1	1	1 - 2	1	1 - 2
1	1	1 - 2	1	1	1	1	1 - 2	1	1 - 2
1		1		1	1	1	1 - 2		1 - 2
	1	2	1	1	1	1	1 - 2	1	1 - 2
1	1	1 - 2	1		1	1	1 - 2		1 - 2
1		1 - 2	1	1	1	1	1 - 2		1 - 2
1	1	1 - 2	1	1	1	1	1 - 2	1	1 - 2
1			1	1	1	1	1 - 2		2
1		1 - 2	1	1	1	1	1 - 2		1 - 2

	<b>MAS LED ExpertColor 6.7-35W MR16</b> 9290030785, 9290030786, 9290030787, 9290030788, 9290030789, 9290030790, 9290030791, 9290030792, 9290030793, 9290030794, 9290030795, 9290030796		
Dimmer	Brand	Model	Load
	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC ] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L,C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4 ~ 200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC ] 315W
	Varilight	HQ3W	[R ] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	35 - 105W	50 - 150W	35 - 105W	50 - 150W	0 - 70W	20 - 70W	35-105W	20 - 70W	20 - 105W
1		1-2	1		1-2	1	1-2	1	1-2
1	1	1	1		1-2	1-2	1-2	1	
1	1	1	1	1	1-2	2	1-2	1	2
1		1		1	1-2	1-2	1-2		1-2
1		2	1	1	1-2	1-2	1-2	1	1-2
1	1	1	1		1-2	1-2	1-2		1-2
1		1	1	1	1-2	1-2	1-2		1-2
1	1	1	1	1	1	1-2	1-2	1	1-2
1		1	1	1	1	1	2	1	
1		1	1	1	1-2	1-2	1-2		1-2

# Professional dimmer transformer compatibility list LED

## Low Voltage range

Key

#	Transformer - dimmer combination is compatible with # of lamp(s) and minimum dimming level is below 30% AND maximum dimming level is at least 80%.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab conditions and might contain faults.</i>
#	Transformer - dimmer combination is compatible with # of lamp(s) and minimum dimming level is between 30% (inclusive) and 50% AND maximum level is above or equal to 70%.	
	Transformer is not compatible.	
	Transformer lamp combination not applicable	
	Transformer lamp combination not tested	



MAS LEDspotLV D 7.5-50W MR16  
9290024919, 9290024920, 9290024921,  
9290024922, 9290024923, 9290024924

Dimmer	Brand	Model	Load
	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L, C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4 ~ 200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC] 315W
	Varilight	HQ3W	[R] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	35 - 105W	50 - 150W	35 - 105W	50 - 150W	0 - 70W	20 - 70W	35-105W	20 - 70W	20 - 105W

1			1		1	1	1-2	1	
1	1	2			1	1	1-2	1	1-2
1	1	1-2	1	1	1	1	1-2	1	1-2
1		1-2		1	1	1	1-2		1-2
1	1	2	1	1	1	1	1-2	1	2
1		1-2	1		1	1	1-2		1-2
1	1	1-2	1	1	1	1	1-2		1-2
1	1	2	1	1	1	1	1-2	1	1-2
1			1	1	1	1	1-2	1	
1		1-2	1	1	1	1	1-2		1-2



MAS LEDspot LV DimTone 7.5-50W MR16 36D  
9290024938

Dimmer	Brand	Model	Load
	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L, C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4 ~ 200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC] 315W
	Varilight	HQ3W	[R] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	35 - 105W	50 - 150W	35 - 105W	50 - 150W	0 - 70W	20 - 70W	35-105W	20 - 70W	20 - 105W

1				1-2	1	1	1-3	1	
1	1-2		1-2	1-2	1-2	1	1-3	1	3
1	2	3	1-2	1-2		1	1-3	1	1-3
1		3	1-2	1-2		1	1-3	1	3
		3	1-2	1-2		1	1-3	1	3
1		3	1-2	1-2	1-2	1	1-3	1	3
1	2	3	1-2	1-2	1-2	1	1-3	1	3
1	2	3	1-2	1-2	1-2	1	1-3	1	3
		3		1-2		1	1-3	1	
1	3	1-3	1-2	1-2	1-2	1	1-3	1	1-3



MAS LEDspotLV DimTone 5.8-35W MR16 36D  
9290024931

Dimmer	Brand	Model	Load
	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L, C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4 ~ 200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC] 315W
	Varilight	HQ3W	[R] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	35 - 105W	50 - 150W	35 - 105W	50 - 150W	0 - 70W	20 - 70W	35-105W	20 - 70W	20 - 105W

1-2		1-3	2	2	2		1-6	1	3
1-2	2								
1-2		1-3	1-2	1-2	1-2	1	1-6	1	
1-2			1-2	1-2	1-2	1	1	1	3
1-2	2		1-2	1-2					3
		1-3	1-2	1-2	1-2	1	1-6	1	3
1-2			1-2	2	2	1	1-6	1	3
		3	1-2	1-2		1	1	1	
1-2		1-3	1-2	1-2	1-2	1	1-6	1	3

# Professional dimmer transformer compatibility list LED

## Low Voltage range

Key

#	Transformer - dimmer combination is compatible with # of lamp(s) and minimum dimming level is below 30% AND maximum dimming level is at least 80%.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab conditions and might contain faults.</i>
#	Transformer - dimmer combination is compatible with # of lamp(s) and minimum dimming level is between 30% (inclusive) and 50% AND maximum level is above or equal to 70%.	
	Transformer is not compatible.	
	Transformer lamp combination not applicable	
	Transformer lamp combination not tested	



MAS LED SPOT VLE D 7.5-50W MR16  
9290024932, 9290024933, 9290024934,  
9290024935, 9290024936, 9290024937

Dimmer	Brand	Model	Load
	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L,C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4 ~ 200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC] 315W
	Varilight	HQ3W	[R ] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	35 - 105W	50 - 150W	35 - 105W	50 - 150W	0 - 70W	20 - 70W	35-105W	20 - 70W	20 - 105W

1		2	1	1	1	1	1-3	1	
	1	1	1						1-3
1		2	1	1		1	3	1	1-3
1		1-2	1	1					3
1		1		1			1-3		3
1		2		1			1-3		3
1			1	1	1	1	1-3	1	3
1		2	1	1		1	1-3	1	3
1			1			1	1-3	1	
1			1						



MAS LED spot VLE D 5.8-35W MR16  
9290024925, 9290024926, 9290024927,  
9290024928, 9290024929, 9290024930

Dimmer	Brand	Model	Load
	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L,C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4 ~ 200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC] 315W
	Varilight	HQ3W	[R ] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	35 - 105W	50 - 150W	35 - 105W	50 - 150W	0 - 70W	20 - 70W	35-105W	20 - 70W	20 - 105W

1		1-2	1-2	2	1			1	2
									1-2
1		2	1-2	1-2	1-2	1	1-2	1	
1		1-2	1-2	1-2	1	1			
1	1-2		1-2	1-2		1			
1		1-2	1-2	1-2	1-2	1			
1		1	1-2						
		2	1-2	1-2	2	1	1-2	1	
1								1	
1			1						



MAS LEDspotLV DimTone 5-35W MR16 36D  
9290019047

Dimmer	Brand	Model	Load
	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L,C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4 ~ 200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC] 315W
	Varilight	HQ3W	[R ] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	35 - 105W	50 - 150W	35 - 105W	50 - 150W	0 - 70W	20 - 70W	35-105W	20 - 70W	20 - 105W

1-2		3	1-2	1-2	2	1-2	1-3	1-2	3
2	2	3	2	2	2	1-2	1-3	1-2	3
1-2	2	3	1-2	2	2	1-2	1-3	1-2	3
1-2		3	1-2	1-2	1-2	1-2	1-3	1-2	3
1-2	2	3	1-2	1-2	1-2	1-2	1-3	1-2	
1-2	2	3	1-2	1-2	2	1-2	1-3	1-2	3
2	2	3	1-2	1	1-2	1-2	1-3	1-2	3
1-2	2		1-2	1-2	2	1-2	1-3	1-2	3
1-2	2	3	1-2	1-2		1-2	1-3	1-2	
1-2	2	3	1-2	1-2	2	1-2	1-3	2	1-3




# Professional dimmer transformer compatibility list LED

## Low Voltage range

Key


#	Transformer - dimmer combination is compatible with # of lamp(s) and minimum dimming level is below 30% AND maximum dimming level is at least 80%.	<i>This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab conditions and might contain faults.</i>
#	Transformer - dimmer combination is compatible with # of lamp(s) and minimum dimming level is between 30% (inclusive) and 50% AND maximum level is above or equal to 70%.	
	Transformer is not compatible.	
	Transformer lamp combination not applicable	
	Transformer lamp combination not tested	



**CorePro LEDcapsule LV 4.2-40W GY6.35 827D**  
9290036090

	Brand	Model	Load
Dimmer	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L, C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4~200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC] 315W
	Varilight	HQ3W	[R] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	35 - 105W	50 - 150W	35 - 105W	50 - 150W	0 - 70W	20 - 70W	35-105W	20 - 70W	20 - 105W
2		1-3	1-3	1-3		1-2	1-3	1-2	
				3		1-2	3	2	
1-2	3	1-3	1-3	1-3		1-2	1-3	1-2	3
1-2		1-3	1-3	1-3	1	1-2	1-3	1-2	1
	3			3	3	1-2	3		
1-2		1-3	1	1-3	1-3	1	1	2	1-3
1-2									
2	3	3	3	3	3	2	3	1-2	1-3
1	1-3		1	1-3		1		1-2	
1-2	1-3	1	1-3	1-3	3	1-2	1-3	1-2	



**LED 20W G4 WW 12V Dim**  
9290037792

	Brand	Model	Load
Dimmer	Legrand	BTN4411N BTNT4411 BTL4411N	5 - 75VA
	Busch Jaeger   ABB	6513 U - 102	[RC] 40 ~ 420 W - Turn
	Busch Jaeger   ABB	6523 UR-103 Trailing Edge	[LED, R, L, C] 2 - 400W - Turn- Leading
	Eltako	EVD61NPN-UC	400W 3-wire Push Module
	Merten  Schneider  Feller	SBD200LED (MEG5134-0000)	[LED/RC] 4~200W(RC) 4~400W(RL)
	Merten  Schneider  Feller	MEG5300-0001 (CCT99100)	[LED, RL, RC] 4 - 20VA RL LED / 4 - 100VA RC LED
	Philips	UID8670	[LED] 2 ~ 100 VA-LED - Push (3wire)
	Schneider  Feller	SBD315RC (SBD 315, SDD 315, ATD315, CCT011533)	[RC] 315W
	Varilight	HQ3W	[R] 60-400W
	Vimar	Universal dimmer 20135.1	[LED] 3 - 200W - Tast

Transformer									
Philips			Osram	Vossloh Schwabe	TCI	Goven		Varilight	Jung
ET-S60	Primaline 70	Certaline 105	HTM 70	EST 70	ROUND 70	YT60	YT105	YT50L	SNT150
20 - 60W	20 - 70W	35 - 105W	20 - 70W	20 - 70W	20 - 70W	0 - 50W	0 - 70W	0-50W	20 - 105W
1-5		3-5	1-5	3-5	3-5	1-5	1-5	1-5	1-3
3-5	5	5	3-5	3	5	3-5	5	5	5
1-5	3-5	3	1-5	1-5	1-5	1-5	3-5	5	
1-5		3-5	1-5	1-5	1-3	1-5	1-5	1-5	3-5
3-5	3-5	3-5	1-5	3-5	3-5	3-5	3-5	3-5	
1-5	3-5	5	1-5	3-5	3-5	5	3-5	1-5	3-5
3-5	3-5	3-5	3-5	3-5	1-5	1-5	1-5	1-5	3-5
5	5		5			3-5	5	3-5	
1-3	3	5	3	1-3	1	1	3-5	1,5	
1-5	3-5		1-5	1-3		5			3-5

- Notes
- Transformers and dimmers are tested with the number of LED light sources mentioned in the tables above. A number of LED light sources outside the listed range may result in less optimal behavior. Although not specifically tested, some combination of dimmers and transformers can be loaded with more light sources than specified in this document.
    - Most (non-LED dedicated) dimmers and or transformers can be loaded with LED light sources up to 20% of dimmer/transformer specified maximum power. Example: Dimmer 400W -> 20% = 80W, which means that e.g. up to 16 pcs 5W LED light sources can be connected.
    - LED dimmers/transformers can be loaded up to the specified maximum dimmer/transformer power (Wattage).
  - Always study the packaging of LED light sources if these can be used in combination with occupancy motion sensors.
  - "Dimming range" color indications and criteria (all percentages relate to the LED light source full power):
    - Green cell: minimum dimming level is below 30% AND maximum level at least 80%.
    - Yellow cell: minimum dimming level is between 30% (inclusive) and 50% AND maximum level is above or equal to 70%.
    - Red cell: not compatible.
    - Grey cell: the dimmer-transformer-LED light source combination is not applicable.
    - White cell: no data available.
    - Single point flicker in the dimming range is acceptable.
  - Various dimmer suppliers offer "active loads" to optimize dimming performance in case of light source-dimmer system issues. (e.g. Busch Jaeger Compensator 6596).
  - This list is based on measurements performed in a lab environment at nominal mains voltage, different mains voltages may result in a different dimming range.
  - Dimmer and or transformer manufacturers may change the technical design of their dimmer/transformer without informing Philips. Such changes may affect the performance when used in combination with LED light sources.
  - In general Philips / Signify dimmable LED light sources can be dimmed with any type of dimmer (type R, RL, RC or RLC).
  - Mixed loads may give unexpected dimming behavior or even result in defects, for which Philips cannot be held responsible.
  - LED light source are dimmable across the indicated dimming range, but may exhibit minor flickering at distinct dim settings.
  - The information contained here is believed to be accurate at the time it was published, but is provided "AS IS".
  - The DALI ET test data is with Dynalite DDBC120-DALI controller under limited conditions. Signify reserves the rights to the final explanation.

